

Specifications

- 6 x 2.3 kW portable digital dimmer-3-key keypad, 4-character LED display and user-friendly menu for easy access to all dimmer functions.
- Local test of a dimmer (steady or chaser).
- 10 dimmer laws selectable per dimmer.
- Fade smoothing (4000-step resolution).
- Last lighting cue maintained in case of DMX signal interruption.
- Permanent storage of all programmed data.
- Protection circuitry against accidental 400 V wiring.
- Local status reporting: 400 V – overtemperature – fan failure – processor check – presence of DMX signal – DMX and analogue control levels.
- First dimmer address selection.
- Storage of a lighting cue.
- Low noise fan for effective cooling with automatic fanstop.
- Overtemperature protection through gradual dimmer fade out.